

OPERATING INSTRUCTIONS

The Crybaby Classic Wah is an amazingly expressive and dynamic effect. For those reasons, the best way to hear what it can do is to plug in and start riffing. To get you going in the right direction, however, here are some tips and tricks:

- 1) You can create cool, Shaft-style lines by pumping the pedal in time with the music.
- 2) Playing a repeating figure while slowly sweeping the pedal from heel to toe and back again will add a filtered, techno flavor to your parts.
- 3) Set the pedal at its halfway point and leave it there—a la Michael Schenker—for a penetrating, midrange heavy tone.

SPECIFICATIONS*

Input Impedance:	1 Megohm
Bypass:	Hardwire DPDT bypass
Signal To Noise:	>102 dB A weighted
Output:	<1 Kohm
Power Requirements:	+9 VDC @ <2.5 milliamps, 5.5 mm x 2.1 mm positive barrel & negative center or standard 9 Volt battery.

* (all specifications +/- 5% unless otherwise stated)



LIVE TO PLAY LIVE®

DUNLOP MANUFACTURING, INC. P.O. BOX 846 BENICIA, CA 94510 U.S.A.
TEL: 1-707-745-2722 FAX: 1-707-745-2658 WWW.JIMDUNLOP.COM

92503002657

cry baby®

Classic



OWNER'S MANUAL

LEGENDARY
ITALIAN-MADE
FASEL INDUCTOR



DPDT
(Double Pole, Double Throw,
Heavy Duty Switch for Transparent
Hardwire Switching)

CE

SET-UP INSTRUCTIONS

- 1) Insert a 9 volt battery or plug in the Dunlop ECB03 AC Adapter (ECB03E for Europe).
- 2) Run a cord from your guitar to the Crybaby Classic instrument jack.
- 3) Run another cord from the Crybaby Classic to your amp.
- 4) Turn on the amplifier.
- 5) To turn the pedal on, push the toe of the pedal down until you feel a click.

Congratulations on your purchase of the Crybaby Classic Wah from Dunlop. Dunlop is the most trusted name in wah pedal manufacturing and the Crybaby Classic is designed to give you unparalleled sound quality and years of dependable service. Please take a minute to read through this manual so you can get the most out of your Crybaby Classic Wah.

When you think about the classic wah-wah sounds of the 60s, you think about British bluesmen and psychedelic American rockers. You probably don't think about Italy. But those Sunshine-y and Foxey tones could not have existed without the Italian company Fasel. Fasel made the inductors that were in the first wah pedals—including the original Crybaby—and those inductors were the key to the pedals' tone, sweep, and voice. For years the Fasel inductors were unavailable, and so was that sound. Not anymore. Your Crybaby Classic with Fasel Inside will faithfully recreate the vocal sweep and lush harmonics from those timeless recordings. Plug in your Crybaby Classic and hear what you've been missing.

BATTERY INSTALLATION

The Crybaby Classic Wah pedal is shipped from the factory without a battery to prevent damage from leakage. A 9-volt battery must be installed to operate the Crybaby Classic unless an AC adapter is used. We recommend using a high quality alkaline battery. To install the battery, remove the battery cover from the bottom plate of the pedal, connect the battery clip, place battery into cavity, and replace battery cover. To maximize battery life, unplug the input when the effect is not in use. The Crybaby Classic uses the Dunlop ECB03 Adapter (ECB03E for Europe), a 9-volt DC regulated AC adapter. Plug is positive on barrel and negative in the center.